

KUEBLER - WIRE ENCODERS B80

SERIE D8.XB1

- Max measuring length 3000 mm
- -20° to +85°C
- Ready speeds up to 10 m / s
- Titan-anodized aluminum housing



Product description

The Kübler wire generators are designed for demanding applications, for example within the machine building segment. The systems are robustly built with aluminum housing resistant to tough environments, they can handle high speed and have long life. The B80 series comes with analogue, incremental or absolute (SSI / BiSS, CANopen, Profibus, EtherCAT, Profinet or DeviceNet) outputs.

Please refer to the images below for ordering information.

| Order code with encoder (incremental, absolute) | | | | Standard variants are represented bold underlined> | | |
|--|-----|---|------|--|------|--|
| D8.XB1 | | .XXXX | | .XXXX | | |
| a | | b | | c | | |
| a <i>Mechanics</i> 2 = interchangeable installation ¹⁾ 4 = fixed installation ²⁾ | | c <i>Encoder used</i> 00 = Sendix 5000 , incremental M3 = Sendix M5863 , absolute F3 = Sendix F5863, absolute 63 = Sendix 5863, absolute M8 = Sendix M5868 , absolute F8 = Sendix F5868 absolute 68 = Sendix 5868, absolute | | d <i>Output circuit</i> depends on the encoder used | | <i>Optional on request</i> - Other measuring ranges - Cable diameter 1 mm - Eyelet or M4 wire fastening instead of wire clip - Modified cable and/or connector orientation - Modified cable outlet direction - Sensor protection level IP67 - Improved linearity (0.02 %) |
| b <i>Measuring range</i> 0100 = 1000 mm 0200 = 2000 mm 0300 = 3000 mm | | e <i>Type of connection</i> depends on the encoder used | | f <i>Resolution / Protocol / Options</i> depends on the encoder used | | |
| Standard resolutions for draw wire with incremental encoder Sendix 5000 | | Standard resolutions for draw wire with absolute encoder Sendix M5863 (12 bit ST) or M5868 (12 bit ST, programmable via bus) | | | | |
| Drum circumference [mm] | 200 | 200 | 200 | Drum circumference [mm] | 200 | |
| Pulses / revolution [ppr] | 200 | 2000 | 4000 | Pulses / revolution [ppr] | 4096 | |
| Pulses / mm | 1 | 10 | 20 | Pulses / mm | 20.5 | |
| Resolution [mm] | 1 | 0.1 | 0.05 | Resolution [mm] | 0.05 | |

**Order code with encoder
(analog, scalable with limit switch function)**

D8.XB1.XXXX.M1XX.XXXX

Standard variants are represented **bold underlined**

a *Mechanics*

- 2 = interchangeable installation ¹⁾
- 4 = fixed installation** ²⁾

b *Measuring range*

- 0100 = 1000 mm
- 0200 = 2000 mm
- 0300 = 3000 mm

c *Encoder used*

- M1 = Sendix M5861, absolute** ³⁾

d *Output circuit*

depends on the encoder used

e *Type of connection*

depends on the encoder used

f *Resolution / Protocol / Options*

depends on the encoder used

Optional on request

- Other measuring ranges
- Cable diameter 1 mm
- Eyelet or M4 wire fastening instead of wire clip
- Modified cable and/or connector orientation
- Modified cable outlet direction
- Sensor protection level IP67

Recommended standard variants (with encoder analog, scalable with limit switch function)

| Order no. draw wire encoder | Mounted encoder | Interface | Power supply | Type of connection | Resolution / Protocol | Option |
|-----------------------------|----------------------------------|---------------------|----------------|----------------------|-----------------------|--|
| D8.xB1.xxxx.M134.3512 | Sendix M5861 (8.M5861.3534.3512) | Analog, 4 ... 20 mA | 10 ... 30 V DC | radial M12 connector | 12 Bit / 4 ... 20 mA | scalable with limit switch function ⁴⁾ |
| D8.xB1.xxxx.M144.4512 | Sendix M5861 (8.M5861.3544.4512) | Analog, 0 ... 10 V | 15 ... 30 V DC | radial M12 connector | 12 Bit / 0 ... 10 V | scalable with limit switch function ⁴⁾ |
| D8.xB1.xxxx.M134.3612 | Sendix M5861 (8.M5861.3534.3612) | Analog, 4 ... 20 mA | 10 ... 30 V DC | radial M12 connector | 12 Bit / 4 ... 20 mA | scalable without limit switch function ⁴⁾ |
| D8.xB1.xxxx.M144.4612 | Sendix M5861 (8.M5861.3544.4612) | Analog, 0 ... 10 V | 15 ... 30 V DC | radial M12 connector | 12 Bit / 0 ... 10 V | scalable without limit switch function ⁴⁾ |

**Order code with analog sensor
(scaled to measuring range)**

D8.3B1.XXXX.XXX.X.0000

a *Measuring range*

- 0100 = 1000 mm
- 0200 = 2000 mm
- 0300 = 3000 mm

b *Analog sensor output / power supply*

- A11 = 4 ... 20 mA / 12 ... 30 V DC
- A22 = 0 ... 10 V / 12 ... 30 V DC
- A33 = potentiometer 1 kΩ / max. 30 V DC

c *Type of connection*

- 1 = axial cable, 2 m PVC
- 3 = axial M12 connector, 4-pin

Optional on request

- Other measuring ranges
- Cable diameter 1 mm
- Eyelet or M4 wire fastening instead of wire clip
- Modified cable and/or connector orientation
- Modified cable outlet direction
- Sensor protection level IP67
- Improved linearity (0.02 %)
- Increased temperature range -40°C ... +85°C and -20°C ... +120°C

| Pin | 1 | 2 | 3 | 4 |
|--------------|-------|--------|--------|----------|
| Cable colour | brown | white | blue | black |
| 0 ... 10V | V+ | Signal | GND | GND Sig. |
| 4 ... 20 mA | V+ | n. c. | Signal | n. c. |
| 1kOhm | V+ | Slider | GND | n. c. |

| Measuring range [mm] | D [mm] |
|----------------------|--------|
| 1000 | 21 |
| 2000 | 35 |
| 3000 | 35 |

| Dimension B depends on the encoder used | |
|---|-------|
| Encoder | B |
| Sendix Incremental (5000) | 54.25 |
| D8.4B1.XXXX.0000.XXXX | |
| Sendix absolute (3863) | 66.75 |
| D8.4B1.XXXX.6300.XXXX | |
| Sendix absolute (3868) | 93.25 |
| D8.4B1.XXXX.6800.XXXX | |

| Sensor type | Measuring length [mm] | B | D |
|---------------|-----------------------|-------|----|
| Potentiometer | 1000 | 74 | 21 |
| | 2000 | 74 | 21 |
| | 3000 | 102.5 | 35 |
| 4 ... 20 mA | 1000 | 87.5 | 21 |
| | 2000 | 87.5 | 21 |
| | 3000 | 102.3 | 35 |